

# PYLE®

PyleAudio.com




**PDWM2135**



**PDWM2140**



**PDWM2145**



**PDWM2135**

**PDWM2140**

**PDWM2145**

**VHF Wireless Microphone Systems**

**USER MANUAL**



Thank you for purchasing this wireless microphone system. This microphone system operates on high-efficiency, low-consumption discharging techniques. Performance features include independent developed mobile frequency compression, expander circuitry, image frequency limiting circuits, multiple-checked silent and noise-free circuits, antenna diversity receiving circuit & switch impact noise defeat circuits.

The PDWM2135/2140/2145 were manufactured to be easy to use and still give you professional performance quality.

### Simple Installation and Operation:

**\*Please note - select models come equipped with different transmitters and microphones**

- Unscrew the bottom of the microphone (or slide open the battery compartment tray of the belt-pack transmitter) to install two 'AA' Batteries. Screw the Battery cap back on.
- Plug your receiving unit into your mixer or amplifier with a 1/4" mono microphone cord.
- Plug the receiving unit into your electrical wall outlet.
- Turn the receiver on by using the on/off switch located at the front of the unit.
- There is a switch located on each of the two microphones that turns each microphone on/off & mutes them individually.

<p><b>PDWM2135</b></p> <p>VHF Narrow Band Receiver System Dual Frequency Design (Channel A/B) High Signal/Noise Ratio Performance Broad Frequency Response Range &amp; Low Distortion Independent Adjustable Volume Control Dual Independent Channel Antennas RF Signal and AF Signal LED Indicators Radio Frequency and Audio Frequency Includes (2) Handheld Microphones</p> <p><b>System Receiver:</b> Channel Frequency: 174~216MHz Sensitivity: -95dBm (S/N:12dB) RF Image Rejection:-75dB Audio Dynamic Range: 95dB T.H.D.: &lt;1% Frequency Stability: ±0.002% S/N Ratio: &gt;70dB Neighboring Channel / Interference: &gt;70dB Frequency Response: 50Hz~15KHz ± 3dB Power: AC 120V, 60Hz Receiver Dimensions (L x W x H): 8.07" x 5.75" x 1.64"</p> <p><b>Microphones:</b> Carrier Frequency:174~216MHz RF Power Output: &gt;13dBm Modulation Degree: &gt;30KHz Power Current: &lt;110mA Frequency Stability: ±0.002% Harmonic at Higher Degree: &lt;60dB Modulation Pattern: FM Battery Powered: Requires 2 x 'AA' Batteries</p>	<p><b>PDWM2140</b></p> <p>VHF Narrow Band Receiver System Dual Frequency Design (Channel A/B) High Signal/Noise Ratio Performance Broad Frequency Response Range &amp; Low Distortion Independent Adjustable Volume Control Dual Independent Channel Antennas RF Signal and AF Signal LED Indicators Radio Frequency and Audio Frequency Includes Handheld Microphone, Body-Pack Transmitter, Lavalier &amp; Headset Mics</p> <p><b>System Receiver:</b> Channel Frequency: 174~216MHz Sensitivity: -95dBm (S/N:12dB) RF Image Rejection:-75dB Audio Dynamic Range: 95dB T.H.D.: &lt;1% Frequency Stability: ±0.002% S/N Ratio: &gt;70dB Neighboring Channel / Interference: &gt;70dB Frequency Response: 50Hz~15KHz ± 3dB Power: AC 120V, 60Hz Receiver Dimensions (L x W x H): 8.07" x 5.75" x 1.64"</p> <p><b>Transmitters:</b> Carrier Frequency:174~216MHz RF Power Output: &gt;13dBm Modulation Degree: &gt;30KHz Power Current: &lt;110mA Frequency Stability: ±0.002% Harmonic at Higher Degree: &lt;60dB Modulation Pattern: FM Battery Powered: Requires 2 x 'AA' Batteries</p>	<p><b>PDWM2145</b></p> <p>VHF Narrow Band Receiver System Dual Frequency Design (Channel A/B) High Signal/Noise Ratio Performance Broad Frequency Response Range &amp; Low Distortion Independent Adjustable Volume Control Dual Independent Channel Antennas RF Signal and AF Signal LED Indicators Radio Frequency and Audio Frequency Includes (2) Body-Pack Transmitter, (2) Lavalier &amp; (2) Headset Mics</p> <p><b>System Receiver:</b> Channel Frequency: 174~216MHz Sensitivity: -95dBm (S/N:12dB) RF Image Rejection:-75dB Audio Dynamic Range: 95dB T.H.D.: &lt;1% Frequency Stability: ±0.002% S/N Ratio: &gt;70dB Neighboring Channel / Interference: &gt;70dB Frequency Response: 50Hz~15KHz ± 3dB Power: AC 120V, 60Hz Receiver Dimensions (L x W x H): 8.07" x 5.75" x 1.64"</p> <p><b>Transmitters:</b> Carrier Frequency:174~216MHz RF Power Output: &gt;13dBm Modulation Degree: &gt;30KHz Power Current: &lt;110mA Frequency Stability: ±0.002% Harmonic at Higher Degree: &lt;60dB Modulation Pattern: FM Battery Powered: Requires 2 x 'AA' Batteries</p>
---	---	--



# Activate Your 1 Year Warranty

# PYLE

PyleAudio.com

## Why Activate & Register?

Online warranty activation offers numerous benefits! Spend a minute and get:

- A one year limited Manufacturer's Warranty with Pyle Audio
- Full customer support, online or by phone
- Access to product manuals, downloads and FAQs

## To Activate Online:

1. Log on to [www.PyleAudio.com](http://www.PyleAudio.com)
2. Sign in (or create an account)
3. Click on 'Product Registration'

This Limited Warranty does not cover any problem that is caused by:

- Conditions, malfunction or damage not resulting from defects in material or workmanship
- Conditions, malfunctions or damage resulting from negligence, improper maintenance or modification

*Sound Around USA shall assume no risk of loss or damage to the Physical Good while in transit to us.*

Should the product fall due to factory defect in material or workmanship, your unit will be repaired or replaced at the sole discretion of Sound Around Inc. To begin the product service or repair request process, follow the steps below:

- Visit [www.PyleAudio.com](http://www.PyleAudio.com)
- Login and goto 'My Account'
- Click on and create a 'Support Ticket'
- Fill in the required information and attach a proof of purchase
- Provide a brief description of the problem and a Pyle support technician will respond to you with further instruction

Upon warranty validation, you will be instructed to carefully pack and ship your product to:

**Sound Around Service Center**  
**1600 63rd Street**  
**Brooklyn, NY 11204**

USED WISELY, YOUR NEW SOUND EQUIPMENT WILL PROVIDE A LIFETIME OF FUN AND ENJOYMENT. A DEFECT IN MANUFACTURING IS ONE THAT THE MANUFACTURER DID NOT DELIBERATELY INTEND AND MAY BE A POSSIBILITY WITH YOUR PURCHASE. OUR OBLIGATION UNDER THIS WARRANTY IS LIMITED TO THE REPAIR OR REPLACEMENT OF THE DEFECTIVE UNIT WHEN IT IS RETURNED TO US PREPAID. THIS WARRANTY WILL BE CONSIDERED VOID IF THE UNIT WAS TAMPERED WITH, IMPROPERLY SERVICED OR SUBJECT TO MISUSE, NEGLIGENCE OR ACCIDENTAL DAMAGE.



## Get a free 3 month warranty extension

Here at Sound Around, we take your feedback very seriously. Customer satisfaction is a top priority and we continually strive to providing the best service we can. We offer a free three month warranty extension -- in addition to your existing manufacturer's warranty -- for all customers who provide a product review of their new Pyle product online. If you experience any issue with your Pyle product, good or bad, let us know and we will help!

### To Participate:

#### 1. Write a customer review

If you purchased the product online, you can leave a product review via online retailer sites like Amazon, Walmart, Sears, etc.

#### 2. Show us your review

Copy and paste the web address link of your review on [www.PyleAudio.com](http://www.PyleAudio.com), under 'Product Registration' and submit.

*\*It's never too late to leave a review, visit us and leave your feedback!*

We fully support this product with warranty repair or replacement service under a one-year manufacturer's warranty covering defects in the product's material or workmanship. If your product is found to have a defect you can request a RMA (Return Merchandise Authorization) request through our website online. This Limited Warranty applies to physical goods, and only for physical goods, purchased from registered retailers of Sound Around USA. This Limited Warranty covers any defects in material or workmanship under normal use during the Warranty Period. During the warranty period, Pyle Audio will repair or replace, at no charge, products or parts of a product that proves defective because of improper material or workmanship under normal use and maintenance. This Limited Warranty is non transferable and can only be claimed by the original customer who must provide valid proof of purchase. The warranty period for physical goods purchased from Pyle Audio is one year beginning from the date of purchase. A replacement physical good or part assumes the remaining warranty of the original physical good or one year from the date of the replacement or repair -- whichever is longer. Please note Pyle Audio will not cover any shipping costs for service or repair. The customer will be asked to provide a specified amount, to cover shipping costs, once the issue is brought to the attention of the technical support team.

EXCEPT TO THE EXTENT PROHIBITED BY APPLICABLE LAW, ALL IMPLIED WARRANTIES (INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE) SHALL BE LIMITED IN DURATION TO THE DURATION OF THIS LIMITED WARRANTY. EXCEPT TO THE EXTENT PROHIBITED BY APPLICABLE LAW, SOUND AROUND USA SHALL NOT BE LIABLE FOR ANY INCIDENTAL, INDIRECT, SPECIAL, OR CONSEQUENTIAL DAMAGES RESULTING FROM ANY BREACH OF EXPRESS OR IMPLIED WARRANTY OR CONDITION, OR UNDER ANY OTHER LEGAL THEORY.



facebook/PYLEaudio



@PYLAudio



youtube/PYLEaudio1